Afinia L801 Operator Level Maintenance

Daily (2 mins):

- Clean printhead
- Wipe out any excess ink or paper dust in the paper path (inside clamshell)

Weekly (5 mins):

- Clean printhead
- Clean inside clamshell
- Clean paper path sensors
- Inspect rollers and paper path

Monthly (45 mins):

- Remove and clean printhead.
  - ***ONLY*** use distilled water and lint free cloth on printheads. Place printhead in orange case for printer cleaning. Be sure to keep printhead hydrated. Remove and clean service tray. Wash service tray component as instructed.
  - ***ONLY*** use distilled water on microfiber roller in service stations. Remove microfiber roller before cleaning wiper transfer module.

Turn off printer before performing cleaning steps below:

- Vacuum out excess dirt and paper dust inside the machine
- Inspect and clean paper path including rollers on the top side of clamshell
- Clean paper path sensors – see instructions
- Clean service station sensors – see instructions
- Clean grit rollers
- Inspect and clean deck around where wick drains off ink out of the service station
- Lubricate service station
- Inspect and clean ink tanks
- Inspect the waste ink absorber and tray